

# PROMAX

## 3500A

### PORTABLE GENERATOR FOR PROFESSIONAL USE

#### PROMAX 3500A ▶▶▶

##### FEATURES:

- Briggs & Stratton Vanguard™ engine
- Automatic Voltage Regulator (AVR)
- Low oil shut-down sensor
- Large Super Lo-Tone™ muffler
- Circuit breaker protected
- 32 mm tubing
- Voltmeter
- Wheelkit optional
- Fuel Gauge
- Warranty 2 years

##### SPECIFICATIONS:

Rated Power ( W )	2700
Equivalent Max. kVA*	3.4
Engine Type / HP**	OHV Vanguard™ / 6.5
Fuel Capacity ( l )	15
Weight ( kg )	51
L x W x H ( cm )	61 x 41 x 51
Run Time @ 50% load	13hr 26min
Consumption @ 50% load	1.12 l/h
Low oil shut down protection system	Yes
Noise level LwA/dB at 7m	96 / 71
Circuit breaker	Yes
Wheelkit	Optional
Voltage / Frequency Continental	230 V / 50 Hz
Voltage / Frequency UK	115 V - 230 V / 50 Hz
Type	Continental, UK, Export

CE



Please refer to page 18-19 for socket types.

- \* Equivalent Max kVA: some manufacturers give ratings in kVA by adding 25% to the power rating. This figure is for comparison with these values.  
 \*\* All power levels are stated gross horsepower per SAE J1940 as rated by Briggs & Stratton.

POWERED BY  
**VANGUARD**  
COMMERCIAL POWER



▶ Large super Lo-Tone™ muffler.



▶ Premium Vanguard™ Engine.

